

Essential Question

How much metal can a current make?

What Is Electrolysis?


- Electrolysis: electrical energy drives a thermodynamically unfavored reaction
- An outside power source pushes the electrons

Galvanic cell
favored reaction
makes electricity
 $E^{\circ} > 0$

Electrolytic cell
electricity forces an
unfavored reaction
 $E^{\circ} < 0$

Electroplating

- The object being plated is the cathode
- $\text{Ag}^+ + \text{e}^- \rightarrow \text{Ag}$ coats the object



Current and Charge

- Current (I): charge that flows per second
- $1\text{ A} = 1\text{ C/s}$

$$I = q / t$$

$$q = I \times t$$

q = charge in coulombs (C)

t = time in seconds (s)

The Faraday Constant

- F = charge on 1 mole of electrons
- Converts coulombs $\leftrightarrow$ moles of e^-

$$1 \text{ mol } e^- = 96,485 \text{ C}$$


$$\begin{aligned} & (1.60218 \times 10^{-19} \text{ C per } e^-) \\ & \times (6.02214 \times 10^{23} e^- \text{ per mol}) \end{aligned}$$

Ion Charge Sets the Electrons

- Ion charge = moles of e^- per mole of metal

Ion	Half-reaction	mol e^- per mol metal
Ag^+	$Ag^+ + e^- \rightarrow Ag$	1
Cu^{2+}	$Cu^{2+} + 2e^- \rightarrow Cu$	2
Al^{3+}	$Al^{3+} + 3e^- \rightarrow Al$	3

The Road Map



Example: Copper Plating

A current of 2.50 A passes through a CuSO_4 solution for 30.0 min. What mass of Cu is plated at the cathode?

$$I = 2.50 \text{ A}$$

$$t = 30.0 \text{ min}$$

$$\text{Cu: } 63.55 \text{ g/mol}$$

Example: Time to Plate Silver

How long, in seconds, does it take to plate 2.00 g of Ag onto a spoon from a solution of Ag^+ using a current of 1.50 A?

$$m = 2.00 \text{ g Ag}$$

$$I = 1.50 \text{ A}$$

$$\text{Ag: } 107.87 \text{ g/mol}$$

Example: Current to Make Aluminum

Aluminum is made by electrolysis of molten Al_2O_3 , which contains Al^{3+} . What current is needed to produce 10.0 g of Al in 1.00 hour?

$$m = 10.0 \text{ g Al}$$

$$t = 1.00 \text{ h}$$

$$\text{Al: } 26.98 \text{ g/mol}$$

Example: Finding the Ion Charge

A current of 0.800 A flows for 45.0 min through a solution of an iron salt, and 0.625 g of Fe is deposited. What is the charge on the iron ion?

$$I = 0.800 \text{ A}$$

$$t = 45.0 \text{ min}$$

$$m = 0.625 \text{ g Fe}$$

$$\text{Fe: } 55.85 \text{ g/mol}$$

Big Ideas

- Electrolysis: electricity drives an unfavored reaction
- $I = q / t$, and $1 \text{ A} = 1 \text{ C/s}$
- $1 \text{ mol e}^- = 96,485 \text{ C}$
- Ion charge = mol e^- per mol metal

